



- **Product Name: High Pass Filter**
- **Model: HXLBQ-GTA39**
- **Frequency: 11~40GHz**

- ★ High Stop Band Rejection
- ★ Low Pass Band Insertion Loss
- ★ Customizable Design
- ★ Small Size

Technical Data Sheet	
Item	Parameters
● Cut Off Frequency	11GHz
● Pass Band Frequency	11 ~ 40GHz
● Pass Band Insertion Loss	≤2.0dB @ 11 ~ 11.8GHz ≤1.0dB @ 11.8 ~ 40GHz
● Pass Band VSWR	≤1.6:1
● Stop Band Attenuation	≥50dB @ DC ~ 9.7GHz
● Impedance	50 Ohms
● Power Handling	15W Max.
● Connectors	2.92mm(K)-Female
● Surface Finish	Guide Oxygen or Painted Black
● Temperature Range	-55°C ~ +85°C
● Net weight	0.01 KG
● <b>Outline Drawing:</b> (Dimensions Unit: mm, Dimensions Tolerance: ±0.5mm)	
◆ <b>Material</b>	<ul style="list-style-type: none"> <li>● Housing: Aluminum alloy</li> <li>● Connectors: Stainless Steel</li> <li>● Screw: Stainless Steel</li> <li>● Dimensions: 15*12.7*10mm</li> </ul>

